

**ORDERING CODE SYSTEM:**

The coded part number are subdivided in 6 groups comprising 10 digits:

1	2	3	4	5	6	7	8	9	10
---	---	---	---	---	---	---	---	---	----

**-Group 1**

The first three digits (1,2,3) indicate series:

- **IZA** is the MKP-69 series printing as DC voltage.
- **IZB** is the MKP-69 series printing as AC voltage.

**-Group 2**

One digit (4) indicate rated voltage.

DIGIT (4)	RATED VOLTAGE
N	250 V
P	300 V
S	400 V
V	630 V
C	850 V
W	1000 V
X	1250 V
Y	1600 V
Z	2000 V
E	3000 V

**-Group 3**

Three digits (5, 6, 7) indicate the rated capacitance. The digit (5) indicates the number of digits in the basic unit pF.

Digit (5)	
5	From 0.01 $\mu$ F to 0.099 $\mu$ F
6	From 0.1 $\mu$ F to 0.99 $\mu$ F
7	From 1 $\mu$ F to 9.9 $\mu$ F
8	From 10 $\mu$ F to 99.9 $\mu$ F

Example.

0.15  $\mu$ F = 150,000 pF (6 digits)  
 47  $\mu$ F = 47,000,000 pF (8 digits)

The digits (6,7) specify the two first numbers of the rated capacitance value.

Example.

22 for 0.0022  $\mu$ F; 33 for 0.33  $\mu$ F; 68 for 68  $\mu$ F

**-Group 4**

One digit (8) indicate the lead spacing or pitch.

Digit (8)	Body Length (L) (mm)
D	13~15
E	16~18
F	19~21
G	22~24
H	25~27
I	28~30
K	31~33
L	34~36
M	37~39
N	40~45
P	46~50
R	51~55
T	56~60

**-Group 5**

One digit (9) indicates the capacitance tolerance:

Digit (9)	Capacitance tolerance
J	5%
K	10%
M	20%

(Standard tolerance 10%)

**-Group 6**

One digit (10) indicates lead style

Digit (10)	Lead style
0	Long straight leads (standard 35 mm long)

**EXAMPLE:**

Code Konek: **IZAN622DK0**

**IZA** → MKT-69 DC voltage, **N** →250V,  
**622**→0.22 $\mu$ F, **D** →13-15mm, **K**→ 10% Tol,  
**0**→Long Leads

Code Konek: **IZBS533GM0**

**IZB** → MKT-69 AC voltage, **S**→400V,  
**533**→0.033 $\mu$ F, **G** →22-24mm, **M**→ 20% Tol,  
**0**→Long Leads

Other values contact us