

ORDERING CODE SYSTEM:

The coded part number are subdivided in 6 groups comprising 10 digits:

1	2	3	4	5	6	7	8	9	10
---	---	---	---	---	---	---	---	---	----

-Group 1

The first three digits (1,2,3) indicate series.

-IAA is the MKT-69 series.

-Group 2

One digit (4) indicate rated voltage.

DIGIT (4)	RATED VOLTAGE
B	50V
H	63V
J	100 V
K	230 VAC
N	250 V
S	400 V
V	630 V
W	1000 V

-Group 3

Three digits (5, 6, 7) indicate the rated capacitance. The digit (5) indicates the number of digits in the basic unit pF.

Digit (5)	
5	From 0.01 ?F to 0.099 ?F
6	From 0.1 ?F to 0.99 ?F
7	From 1 ?F to 9.9 ?F
8	From 10 ?F to 99.9 ?F

Example.

0.15 ?F = 150,000 pF (6 digits)
47 ?F = 47,000,000 pF (8 digits)

The digits (6,7) specify the two first numbers of the rated capacitance value.

Example.

22 for 0.0022 ?F; 33 for 0.33 ?F.

-Group 4

One digit (8) indicate the lead spacing or pitch.

Digit (8)	Body Length (L) (mm)
D	13?15
E	16?18
F	19?21
G	22?24
H	25?27
I	28?30
K	31?33
L	34?36
M	37?39
N	40?45
P	46?50
R	51?55
T	56?60

-Group 5

One digit (9) indicates the capacitance tolerance:

Digit (9)	Capacitance tolerance
J	5%
K	10%
M	20%

(Standard tolerance 10%)

-Group 6

One digit (10) indicates lead style

Digit (10)	Lead style
0	Long straight leads (35 ? 5 mm)

EXAMPLE:

Code Konek: **IAAJ622DK0**

IAA ? MKT-69, J ? 100V, 622? 0.22?F,
D ? 13-15mm, K? 10% Tol, 0? Long Leads

Code Konek: **IAAS733KM0**

IAA ? MKT-69, S ? 400V, 733? 3.3 ?F,
K? 31-33mm, M? 20% Tol, 0? Long Leads

Other values contact us