

ORDERING CODE SYSTEM:

The coded part number are subdivided in 6 groups comprising 10 digits:

1	2	3	4	5	6	7	8	9	10
---	---	---	---	---	---	---	---	---	----

-Group 1

The first three digits (1,2,3) indicate series:

- **IYA** is the MKP-70 series printing as DC voltage.
- **IYB** is the MKP-70 series printing as AC voltage.

-Group 2

One digit (4) indicate rated voltage.

DIGIT (4)	RATED VOLTAGE
N	250 V
S	400 V
V	630 V
W	1000 V

-Group 3

Three digits (5, 6, 7) indicate the rated capacitance. The digit (5) indicates the number of digits in the basic unit pF.

Digit (5)	
5	From 0.01 ?F to 0.099 ?F
6	From 0.1 ?F to 0.99 ?F
7	From 1 ?F to 9.9 ?F
8	From 10 ?F to 99.9 ?F

Example.

0.15 ?F = 150,000 pF (6 digits)
47 ?F = 47,000,000 pF (8 digits)

The digits (6,7) specify the two first numbers of the rated capacitance value.

Example.

22 for 0.0022 ?F; 33 for 0.33 ?F.

-Group 4

One digit (8) indicate the lead spacing or pitch.

Digit (8)	Body Length (L) (mm)
D	13? 15
E	16? 18
F	19? 21
G	22? 24
H	25? 27
I	28? 30
K	31? 33
L	34? 36
M	37? 39
N	40? 45
P	46? 50
R	51? 55
T	56? 60

-Group 5

One digit (9) indicates the capacitance tolerance:

Digit (9)	Capacitance tolerance
J	5%
K	10%
M	20%

(Standard tolerance 10%)

-Group 6

One digit (10) indicates lead style

Digit (10)	Lead style
0	Long straight leads(standard 35 mm long)

EXAMPLE:

Code Konek: **IYAN622DK0**

IYA ? MKP-70 DC voltage, **N**? 250V, **622**? 0.22? F
D? 13-15mm, **K**? 10% Tol, **0**? Long Leads

Code Konek: **IYBS733HM0**

IYB ? MKP-70 AC voltage, **S**? 400V, **733**? 3.3?F,
H ? 25-27 mm, **M**? 20% Tol, **0**? Long Leads

Other values contact us