

**ORDERING CODE SYSTEM:**

The coded part number are subdivided in 6 groups comprising 10 digits:

1	2	3	4	5	6	7	8	9	10
---	---	---	---	---	---	---	---	---	----

**-Group 1**

The first three digits (1,2,3) indicate series.

-**IBA** is the MKT-70 series

**-Group 2**

One digit (4) indicate rated voltage.

DIGIT (4)	RATED VOLTAGE
J	100 V
N	250 V
S	400 V
V	630 V
W	1000 V

**-Group 3**

Three digits (5, 6, 7) indicate the rated capacitance. The digit (5) indicates the number of digits in the basic unit pF.

Digit (5)	
5	From 0.01 ?F to 0.099 ?F
6	From 0.1 ?F to 0.99 ?F
7	From 1 ?F to 9.9 ?F
8	From 10 ?F to 99.9 ?F

Example

0.15 ?F = 150,000 pF (6 digits)  
47 ?F = 47,000,000 pF (8 digits)

The digits (6,7) specify the two first numbers of the rated capacitance value.

Example.

22 for 0.022 ?F; 33 for 0.33 ?F; 68 for 68 ?F

**-Group 4**

One digit (8) indicate the lead spacing or pitch.

Digit (8)	Body Length (L) (mm)
D	13? 15
E	16? 18
F	19? 21
G	22? 24
H	25? 27
I	28? 30
K	31? 33
L	34? 36
M	37? 39
N	40? 45
P	46? 50
R	51? 55
T	56? 60

**-Group 5**

One digit (9) indicates the capacitance tolerance:

Digit (9)	Capacitance tolerance
J	5%
K	10%
M	20%

(Standard tolerance 10%)

**-Group 6**

One digit (10) indicates lead style

Digit (10)	Lead style
0	Long straight leads(standard 35 mm long)

**EXAMPLE:**

Code Konek: **IBAJ622DK0**

**IBA** ? MKT-70, **J** ? 100V, **622?** 0.22?F,  
**D** ? 13-15mm, **K** ? 10% Tol, **0?** Long Leads

Code Konek: **IBAN733HM0**

**IBA** ? MKT-70, **N** ? 250V, **733?** 3.3 ?F,  
**H** ? 25-27mm, **M** ? 20% Tol, **0?** Long Leads

Other values contact us